HIGH VOLTAGE DC ADAPTER


Image: Stress of the stres of the stress of the stress of the stress

- High Voltage DC Adater
- Input voltage up to 1000VDC
- Output voltage up to 100VDC

Specifications

| Input Voltage: | 0- 1000VDC |
|--------------------|-----------------|
| Output Voltage: | 0-100VDC |
| Temperature range: | -10 to +54°C |
| Dimensions: | 55 x 110 x 75mm |
| Weight: | 0,4kg |

Dimension



Connection Diagram Input: 0-1000VDC 1 2 NEG POS IN IN **RH1000S** NEG POS OUT OUT 6 4 Output: 0-100VDC ÷ V 1000 **`**500 \mathbf{O} megacon PQ96C

Input: 0-100VDC Scale: 0-1000VDC

Norway Denmark United Kingdom



www.megacon.com

ELECTRONIC CONTROL AND INSTRUMENTATION

REF: Datasheet.RH1000S - REV: 1.01/03.2019 © All rights reserved to Megacon Megacon reserves the right to make any changes to the information at any time

CE

RH1000S